

## Dante 2 CH Analog Input Adapter



SHENZHEN S-TRACK SCIENCE & TECHNOLOGY CO., LTD. is top 3 audio system manufacturer and supplier in China. S-TRACK® Dante 2 CH Analog Input Adapter(DI 22), some country call it AVIO, some customer name it Dante interface,they are all same. S-TRACK® Dante 2 CH Analog Input Adapter(DI 22) extends audio, control, Ethernet and power with an affordable network cable.

## S-TRACK® Dante 2 CH Analog Input Adapter(DI 22)

### Product Introduction:

S-TRACK® Dante 2 CH Analog Input Adapter(DI 22) is compact, easy to use, and supports hot-plugging, making it easy and free to convert between analog and Dante digital audio signals, and fully supports Dante software to easily expand and configure network and audio routing with just a few mouse clicks.

## S-TRACK® Dante 2 CH Analog Input Adapter(DI 22)

### Product Parameters:

Three-conductor Connector	XLR Female	2 pcs
RJ45 Network Port		1pc
Analog Audio Interface		XLR connector

Dante Network Audio Interface	RJ45
Power Consumption	<1W
Maximum Signal Level (balanced)	18dBu
Frequency Response	20-20KHz, $\pm 0.5$ dB
Impedance	20K $\Omega$ (balanced)
Impedance	10K $\Omega$ (unbalanced)
Dynamic Range	> 100dB
Signal to Noise Ratio	> 100dB
THD+N	< 0.003%@4dBu,1KHz
Connector	RJ45 and 1XLR-F; RJ45 and 2XLR-F
Sampling Rate	48KHz
Network Transmission	Dante IP Chinese Dante(AES67) RTP Audio
Background Noise	-90dBu
Dimensions (LxWxH)	652mm x 32mm x 22mm
Weight	0.2kg

## S-TRACK® Dante 2 CH Analog Input Adapter(DI 22)

### Product Features:

★1. Two analog audio signal inputs and two Dante network audio signal outputs are supported.

★2. Two XLR male connectors for analog audio signal input.

Shenzhen S-Track Science&Technology Co.,Ltd

Tel: +86-13302998794

E-mail: [travis@s-track.cn](mailto:travis@s-track.cn)

★3. 1 RJ45 network port connected to the switch for the output Dante network audio signal.

4. Convert the analog audio signal to Dante network audio signal output.

## **S-TRACK® Dante 2 CH Analog Input Adapter(DI 22)**

### **Applications:**

S-TRACK® Dante 2 CH Analog Input Adapter(DI 22) is suitable for meeting room, exhibition hall, small activities, classroom interaction and other occasions.

